


## Comm Server - Download

Perform the following steps to download the Comm Server as a partial into Group 1.

Terminal Displays	Action Taken
SYS MODE MENU 1 EDIT PARAMETERS DOWNLOAD RESTART ▼	Press the Purple button below the Down [ ▼ ] Arrow at the bottom of the display once.
SYS MODE MENU 2 MEMORY FUNCTIONS TERMINAL INFO CLOCK ▲ ▼	Press the [F2] button.
SYS MODE MEM FUNCS RAM: 2048 FLASH: 4096 USAGE DIRECTORIES CLEAR MEM ▼	Press the [F2] button.
MEMORY USAGE RAM FILES 105 INUSE 957218 KB <b>AVAIL 1079198 KB</b> FLASH FILES 149 INUSE 1661080 KB <b>AVAIL 108384 KB</b>	Press the Red [X] button once.  <b>Verify whether RAM or FLASH (Shown in red) memory has more available, this information will be used later in these download instructions.</b>
SYS MODE MEM FUNCS RAM: 2048 FLASH: 4096 USAGE DIRECTORIES CLEAR MEM ▼	Press the Red [X] button once.
SYS MODE MENU 2 MEMORY FUNCTIONS TERMINAL INFO CLOCK ▲ ▼	Press the Purple button below the Up [ ▲ ] arrow at the bottom of the display once.
SYS MODE MENU 1 EDIT PARAMETERS DOWNLOAD RESTART ▼	Press the [F3] button.
SYS MODE FILE FILE GROUP _1	Press the Green [Enter] button.
SYS MODE FILE GROUP 1 PASSWORD _____	Key in 1, Alpha, Alpha, 66831 and press the Green [Enter] button.
SYS MODE DOWNLOAD G 1 FULL PARTIAL	Press the [F4] button.
SYS MODE DOWNLOAD G 1 MODEM COM1 TCPIP ▼	Press the [F2] button.
SYS MODE DOWNLOAD G 1 *ZP HOST PHONE NUMBER _____	Key in <b>18778613835</b> or 9,18778613835 and press the Green [Enter] button.

<p>SYS MODE DOWNLOAD *ZT ENTER TERMINAL ID _____</p>	<p>G 1</p>	<p>F1 F2 F3 F4</p>	<p>If you have more RAM, key in <b>UCSE1R305</b> and press the Green [Enter] button.</p>  <p>If you have more FLASH, key in UCSE1F305 and press the Green [Enter] button.</p>
<p>SYS MODE DOWNLOAD *ZA ENTER APPLICATION _____</p>	<p>G 1</p>	<p>F1 F2 F3 F4</p>	<p>Key in <b>UCSE1R305</b> or UCSE1F305 (same as *ZT above) and press the Green [Enter] button.</p>
<p>SYS MODE DOWNLOAD *ZA = UCSE1R305 *ZP = 18778613835 *ZR = 6 *ZT = UCSE1R305</p>	<p>G 1</p>	<p>F1 F2 F3 F4</p>	<p>Review the download parameters. If correct, press the [F4] button.</p>
<p>SYS MODE DOWNLOAD APP ID: UCSE1R305 STATUS: CONNECTING. . . .</p>	<p>G1</p>	<p>F1 F2 F3 F4</p>	<p>The terminal will now dial into the host to load the application.</p>
<p>SYS MODE DOWNLOAD GID:1 APP ID: UCSE1R305 STATUS: DOWNLOADING. . . -----</p>	<p>G1</p>	<p>F1 F2 F3 F4</p>	<p>You will see a series of Dashes appear on the screen. As the download completes, the dashes will begin turning into asterisks. Each Asterisk [*] represents 10% of the download.</p>
<p>SYS MODE DOWNLOAD GID:1 APP ID: UCSE1R305 STATUS: DOWNLOADING. . . . DOWNLOAD DONE</p>	<p>G1</p>	<p>F1 F2 F3 F4</p>	<p>Press the Green [Enter] button to validate the download. The terminal will reboot and complete the installation of the new application.</p>
<p>02/30/12 10:23:35 COMMSERVER CREDIT/DEBIT CHECKS</p>		<p>F1 F2 F3 F4</p>	<p>The terminal is now ready to process via IP.</p>